DTK-7VS

7-Outlet Surge Protective Device



DITEK's DTK-7VS power strips are the next wave in power distribution devices that combine DITEK's trusted surge protection with a modern look and feel. Your sensitive electronics are safe with features like an illuminated load-status indicator and resettable overcurrent protection.

Is your circuit overloaded? Now you know the answer. Green = Safe; Orange = Warning; Red = Maximum, Flashing Red = Overload.

PRODUCT FEATURES

- (7) 120Vac outlets
- 4' power cord
- Illuminated load-status indicator with different colors for each level of load status
- 2-in-1 power ON/OFF rocker switch

APPLICATIONS

- Audio/Video Equipment
- Point of Use Appliances

TECHNICAL SPECIFICATIONS	
Service Voltage:	120Vac Single Φ
Surge Current Rating:	36,000A
Max. Continuous Current:	15 amps
Nominal Discharge Current Rating (I_n):	3kA
MCOV:	127V
Voltage Protection Rating (VPR):	500V Line-Ground 500V Neutral-Ground 500V Line-Neutral
Operating Frequency:	50/60Hz
Status Indication:	LED

DITEK Surge Protection, Largo, FL 33771 • Sales: 800-753-2345
Diteksurgeprotection.com • SPS-100083-002 Rev 6 05/26

c UL us LISTED

Every precaution has been taken to ensure that this is accurate and complete. DITEK Corporation assumes no responsibility and disclaims all liability for damages resulting from the use of this information or for any errors or omissions.

DTK-7VS

7-Outlet Surge Protective Device

MECHANICAL SPECIFICATIONS	
Connection Method:	NEMA 5-15P 4-foot cord
Housing:	ABS
Operating Temperature:	32°F – 77°F (0°C – 25°C)
Maximum Humidity:	95% non-condensing
Dimensions:	13 in. L x 2.25 in. W x 1.25 in. H (330 mm x 57 mm x 32 mm)
Weight:	17.6 oz. (499g)

SAFETY STANDARDS AND CERTIFICATIONS	
Certifications:	UL 1449 4th Edition Type 3 SPD CSA C22.2 No. 269.1-17, 2017-02
Standards Compliance:	RoHS
Warranty:	10 Year Limited Warranty

DITEK Surge Protection, Largo, FL 33771 • Sales: 800-753-2345
Diteksurgeprotection.com • SPS-100083-002 Rev 6 05/26

c UL us LISTED

Every precaution has been taken to ensure that this is accurate and complete. DITEK Corporation assumes no responsibility and disclaims all liability for damages resulting from the use of this information or for any errors or omissions.